



# MSTronic Co., Ltd.

2F, 12, Gongshang Rd., Wugu Township, Taipei County, Taiwan

TEL:886-2-2293-0159 FAX:886-2-2292-8851

E.MAIL: mse@mstronictaiwan.com

WEB: <http://www.mse.com.tw>

## MIT-14-24 PoE Injector

### SPECIFICATION

#### 1. INPUT :

- 1.1 Input Voltage: 9Vdc to 36Vdc
- 1.2 Input Current:
  - 2.05A at 12Vdc
  - (2.86A at 9Vdc)
  - 1.0A at 24Vdc
  - (0.67A at 36Vdc)



#### 2. OUTPUT :

##### 2.1 Output Voltage & Current:

OUTPUT	+24V
Max. load	0.8A
Power	19.2W
Min. Load	0.01A
Load reg. %	5%
Line reg. %	1%
Ripple %	1%
Noise %	1%

TOTAL POWER : 19.2W

Note 1: Noise bandwidth is from DC to 20Mhz. Ripple & Noise is measured by Paralleling a 0.1uF metalize capacitor on the test point.

3. EFFICIENCY : 75% min at Full Load , 12Vdc & 24Vdc Input Voltage

#### 4. PROTECTION

##### 4.1 Short Circuit Protection

Output Short GND Terminal will not damage the Power Supply and will Auto-Reset.

##### 4.2 Input have Fuse Protection.

4.3 Safety Standard : meet UL1950, CSA 22.2 & TUV EN60950.

4.4 EMC : meet FCC Class B , EN55022 Class B ,

4.5 Over Current : 120% ~ 160% @12Vdc Input F.L

4.6 Dual Input Pin & Reverse Protection-----NO Work



# MSTronic Co., Ltd.

2F, 12, Gongshang Rd., Wugu Township, Taipei County, Taiwan

TEL:886-2-2293-0159 FAX:886-2-2292-8851

E.MAIL: mse@mstronictaiwan.com

WEB: http://www.mse.com.tw

## 5. GENERAL DESCRIPTION

- 5.1 Operation Temperature: - 25 - +50 Degree
- 5.2 Storage Temperature: -40 - +80 Degree
- 5.3 Operation Humidity: 5% - 90%
- 5.4 Cooling: Free air cooling
- 5.5 SIZE : 86\*76\*36 (L)\*(W)\*(H) unit: m/m

## 6. Indication :

6.1 Output OK the LED will be "GREEN"

## 7 CONNECTED :

RJ45 Connected and pin out:

RJ-45 Input (Data Only)			RJ-45 Output (Data & Power)	
Pin	Symbol	Description	Symbol	Description
1	RX+	Data Receive	RX+	Data Receive
2	RX-	Data Receive	RX-	Data Receive
3	TX+	Data Transmit	TX+	Data Transmit
4	NC	Not Connector	-Vdc	Feeding power(+)
5	NC	Not Connector	-Vdc	Feeding power(+)
6	TX-	Data Transmit	TX-	Data Transmit
7	NC	Not Connector	(-Vdc)_return +	Feeding power(-)
8	NC	Not Connector	(-Vdc)_return +	Feeding power(-)

Note :

- 1. DC output GND and Vin+/- should not be shorted to ground(FG).
- 2. INPUT CONNERTER :

